

NCP2993

1.3 Watt Audio Power Amplifier with Selectable Fast Turn On Time

The NCP2993 is an audio power amplifier designed for portable communication device applications such as mobile phone applications. The NCP2993 is capable of delivering 1.3 W of continuous average power to an 8.0 Ω BTL load from a 5.0 V power supply, and 1.1 W to a 4.0 Ω BTL load from a 3.6 V power supply.

The NCP2993 provides high quality audio while requiring few external components and minimal power consumption. It features a low-power consumption shutdown mode, which is achieved by driving the SHUTDOWN pin with logic low.

The NCP2993 contains circuitry to prevent from “pop and click” noise that would otherwise occur during turn-on and turn-off transitions. It is a zero pop noise device when a single ended or a differential audio input is used.

For maximum flexibility, the NCP2993 provides an externally controlled gain (with resistors). In addition, it integrates 2 different Turn On times (15 ms or 30 ms) adjustable with the TON pin.

Due to its superior PSRR, it can be directly connected to the battery, saving the use of an LDO.

This device is available in a 9-Pin Flip-Chip CSP package with a 0.4mm pitch (Lead-Free).

Features

- 1.3 W to an 8.0 Ω BTL Load from a 5.0 V Power Supply
- Best-in-Class PSRR: up to -88 dB, Direct Connection to the Battery
- Zero Pop Noise Signature with a Single Ended Audio Input
- Ultra Low Current Shutdown Mode: 10 nA
- 2.5 V–5.5 V Operation
- External Gain Configuration Capability
- External Turn-on Time Configuration Capability: 15 ms or 30 ms
- Thermal Overload Protection Circuitry
- This is a Pb-Free Device*

Typical Applications

- Portable Electronic Devices
- PDAs
- Wireless Phones

*For additional information on our Pb-Free strategy and soldering details, please download the ON Semiconductor Soldering and Mounting Techniques Reference Manual, SOLDERRM/D.




ON Semiconductor®

<http://onsemi.com>

MARKING DIAGRAM




WLCSP9
FC SUFFIX
CASE 499BM



2993 = Specific Device Code
A = Assembly Location
Y = Year
WW = Work Week
▪ = Pb-Free Package

PIN CONNECTIONS



BYPASS OUTB SHUTDOWN
(Top View)

ORDERING INFORMATION

See detailed ordering and shipping information in the package dimensions section on page 11 of this data sheet.

NCP2993




Figure 1. Typical Audio Amplifier Application Circuit with Single Ended Input




Figure 2. Typical Audio Amplifier Application Circuit with a Differential Input

NCP2993

PIN DESCRIPTION

| Pin | Name | Type | Description |
|-----|----------|------|---|
| A1 | INM | I | Negative input of the first amplifier, receives the audio input signal. Connected to the feedback resistor R_f and to the input resistor R_{in} . |
| A2 | OUTA | O | Negative output of the NCP2993. Connected to the load and to the feedback resistor R_f . |
| A3 | INP | I | Positive input of the first amplifier, receives the common mode voltage. |
| B1 | VM | I | Analog Ground. |
| B2 | TON | I | TON pin selects 2 different Turn On times: TON = GND \rightarrow 30 ms TON = VP \rightarrow 15 ms |
| B3 | VP | I | Positive analog supply of the cell. Range: 2.5 V–5.5 V. |
| C1 | BYPASS | I | Bypass capacitor pin which provides the common mode voltage ($V_p/2$). |
| C2 | OUTB | O | Positive output of the NCP2993. Connected to the load. |
| C3 | SHUTDOWN | I | The device enters in shutdown mode when a low level is applied on this pin. |

MAXIMUM RATINGS (Note 1)

| Rating | Symbol | Value | Unit | |
|---|---------------------------------|------------------------|------|---|
| Supply Voltage | V_p | 6.0 | V | |
| Operating Supply Voltage | Op V_p | 2.5 to 5.5 V | – | |
| Input Voltage | V_{in} | –0.3 to $V_{CC} + 0.3$ | V | |
| Power Dissipation (Note 2) | P_d | Internally Limited | – | |
| Operating Ambient Temperature | T_A | –40 to +85 | °C | |
| Max Junction Temperature | T_J | 150 | °C | |
| Storage Temperature Range | T_{stg} | –65 to +150 | °C | |
| Thermal Resistance Junction–to–Air | $R_{\theta JA}$ | (Note 3) | °C/W | |
| ESD Protection | Human Body Model (HBM) (Note 4) | – | 2000 | V |
| | Machine Model (MM) (Note 5) | – | 200 | |
| Latchup Current @ $T_A = 85^\circ\text{C}$ (Note 6) | – | ± 100 | mA | |

Stresses exceeding Maximum Ratings may damage the device. Maximum Ratings are stress ratings only. Functional operation above the Recommended Operating Conditions is not implied. Extended exposure to stresses above the Recommended Operating Conditions may affect device reliability.

1. Maximum electrical ratings are defined as those values beyond which damage to the device may occur at $T_A = +25^\circ\text{C}$.
2. The thermal shutdown set to 160°C (typical) avoids irreversible damage on the device due to power dissipation.
3. The $R_{\theta JA}$ is highly dependent of the PCB Heatsink area. For example, $R_{\theta JA}$ can equal 195°C/W with 50 mm^2 total area and also 135°C/W with 500 mm^2 . The bumps have the same thermal resistance and all need to be connected to optimize the power dissipation.
4. Human Body Model, 100 pF discharge through a $1.5\text{ k}\Omega$ resistor following specification JESD22/A114.
5. Machine Model, 200 pF discharged through all pins following specification JESD22/A115.

NCP2993

ELECTRICAL CHARACTERISTICS Limits apply for T_A between -40°C to $+85^{\circ}\text{C}$ (Unless otherwise noted).

| Characteristic | Symbol | Conditions | Min (Note 6) | Typ | Max (Note 6) | Unit |
|------------------------------------|----------------|--|----------------------|-------------|-----------------|--------------------|
| Supply Quiescent Current | I_{dd} | $V_p = 2.5\text{ V}$, No Load | - | 1.8 | 3.5 | mA |
| | | $V_p = 5.0\text{ V}$, No Load | - | 1.95 | | |
| | | $V_p = 2.5\text{ V}$, $8\ \Omega$ $V_p = 5.0\text{ V}$, $8\ \Omega$ | - | 1.8 1.95 | 3.5 | |
| Common Mode Voltage | V_{cm} | - | - | $V_p/2$ | - | V |
| Shutdown Current | I_{SD} | - | - | 0.02 | 0.5 | μA |
| Shutdown Pull-Down | R_{SD} | - | - | 300 | - | k Ω |
| Shutdown Voltage High | V_{SDIH} | - | 1.2 | - | - | V |
| Shutdown Voltage Low | V_{SDIL} | - | - | - | 0.4 | V |
| Turn On Time (Note 8) | T_{WU} | TON = GND | - | 30 | - | ms |
| | | TON = VP | - | 15 | | |
| Turn Off Time | T_{OFF} | - | - | 1.0 | - | μs |
| Output Impedance in Shutdown Mode | Z_{SD} | - | - | 8.5 | - | k Ω |
| Output Swing | $V_{loadpeak}$ | $V_p = 2.5\text{ V}$, $R_L = 8.0\ \Omega$ | 1.9 | 2.3 | - | V |
| | | $V_p = 5.0\text{ V}$, $R_L = 8.0\ \Omega$ (Note 7) $T_A = +25^{\circ}\text{C}$ | 3.8 | 4.6 | - | |
| RMS Output Power | P_O | $V_p = 2.5\text{ V}$, $R_L = 4.0\ \Omega$ THD + N < 1% | - | 0.5 | - | W |
| | | $V_p = 2.5\text{ V}$, $R_L = 8.0\ \Omega$ THD + N < 1% | - | 0.32 | - | |
| | | $V_p = 5.0\text{ V}$, $R_L = 8.0\ \Omega$ THD + N < 1% | - | 1.3 | - | |
| Maximum Power Dissipation (Note 8) | P_{Dmax} | $V_p = 5.0\text{ V}$, $R_L = 8.0\ \Omega$ | - | - | 0.65 | W |
| Output Offset Voltage | V_{OS} | $V_p = 2.5\text{ V}$ $V_p = 5.0\text{ V}$ | - | 1.0 | - | mV |
| Signal-to-Noise Ratio | SNR | $V_p = 2.5\text{ V}$, $G = 2.0$ 20 Hz < F < 20 kHz | - | 91 | - | dB |
| Positive Supply Rejection Ratio | PSRR V+ | $G = 2.0$, $R_L = 8.0\ \Omega$ $C_{by} = 1.0\ \mu\text{F}$ Input Grounded F = 217 Hz | - | -88 | - | dB |
| | | | $V_p = 5.0\text{ V}$ | - | -88 | - |
| | | | $V_p = 4.2\text{ V}$ | - | -88 | - |
| | | $V_p = 3.0\text{ V}$ | - | -88 | - | |
| | | F = 1.0 kHz | $V_p = 5.0\text{ V}$ | - | -88 | - |
| | | | $V_p = 4.2\text{ V}$ | - | -88 | - |
| $V_p = 3.0\text{ V}$ | - | | -88 | - | | |
| Efficiency | η | $V_p = 2.5\text{ V}$, $P_{orms} = 320\text{ mW}$ | - | 70 | - | % |
| | | $V_p = 5.0\text{ V}$, $P_{orms} = 1.0\text{ W}$ | - | 60 | - | |
| Thermal Shutdown Temperature | T_{sd} | - | - | 160 | - | $^{\circ}\text{C}$ |
| Total Harmonic Distortion | THD | $V_p = 2.5\text{ V}$, F = 1.0 kHz $R_L = 4.0\ \Omega$, $A_V = 2.0$ $P_O = 0.32\text{ W}$ | - | - | - | % |
| | | | - | 0.015 | - | |
| | | $V_p = 5.0\text{ V}$, F = 1.0 kHz $R_L = 8.0\ \Omega$, $A_V = 2.0$ $P_O = 1.0\text{ W}$ | - | - | - | |
| | | | - | 0.01 | - | |

6. Min/Max limits are guaranteed by design, test or statistical analysis.

7. This parameter is guaranteed but not tested in production in case of a 5.0 V power supply.

8. See page 10 for a theoretical approach of this parameter.

TYPICAL CHARACTERISTICS




Figure 3. THD+N vs. Frequency, Single-Ended Input




Figure 4. THD+N vs. Frequency, Single-Ended Input




Figure 5. THD+N vs. Frequency, Single-Ended Input




Figure 6. THD+N vs. Frequency, Single-Ended Input




Figure 7. THD+N vs. Frequency, Single-Ended Input




Figure 8. THD+N vs. Frequency, Single-Ended Input

TYPICAL CHARACTERISTICS




Figure 9. THD+N vs. Frequency, Differential Input




Figure 10. THD+N vs. Frequency, Differential Input




Figure 11. THD+N vs. Frequency, Differential Input




Figure 12. THD+N vs. Frequency, Differential Input




Figure 13. THD+N vs. Frequency, Differential Input




Figure 14. THD+N vs. Frequency, Differential Input

NCP2993

TYPICAL CHARACTERISTICS




Figure 15. THD+N vs. P_{out}




Figure 16. THD+N vs. P_{out}




Figure 17. PSRR vs. Frequency




Figure 18. PSRR vs. Frequency

NCP2993

TYPICAL CHARACTERISTICS




Figure 19. PSRR vs. Frequency




Figure 20. PSRR vs. Frequency




Figure 21. PSRR vs. Frequency




Figure 22. PSRR vs. Frequency




Figure 23. Power Dissipation vs. P_{out}

NCP2993




Figure 24. Maximum Output Power vs. V_P




Figure 25. SNR vs. Frequency

APPLICATION INFORMATION

Detailed Description

The NCP2993 audio amplifier can operate under 2.5 V until 5.5 V power supply. With less than 1% THD + N, it can deliver up to 1.35 W RMS output power to an 8.0 Ω load ($V_P = 5.0$ V). If application allows to reach 10% THD + N, then 1.65 W can be provided using a 5.0 V power supply.

The structure of the NCP2993 is basically composed of two identical internal power amplifiers; the first one is externally configurable with gain-setting resistors R_{in} and R_f (the closed-loop gain is fixed by the ratios of these resistors) and the second is internally fixed in an inverting unity-gain configuration by two resistors of 20 k Ω . So the load is driven differentially through OUTA and OUTB outputs. This configuration eliminates the need for an output coupling capacitor.

Internal Power Amplifier

The output PMOS and NMOS transistors of the amplifier were designed to deliver the output power of the specifications without clipping. The channel resistance (R_{on}) of the NMOS and PMOS transistors does not exceed 0.6 Ω when they drive current.

The structure of the internal power amplifier is composed of three symmetrical gain stages, first and medium gain stages are transconductance gain stages to obtain maximum bandwidth and DC gain.

Turn-On and Turn-Off Transitions

When a shutdown low level is applied, the output level is tied to Ground on each output after 10 μ s.

With $T_{ON} = GND$, turn on time is set to 30 ms. With $T_{ON} = V_P$, turn on time is set to 15 ms. To avoid any pop and click noises, $R_{in} * C_{in} < 2.4$ ms with $T_{ON} = GND$ and $R_{in} * C_{in} < 1.2$ ms with $T_{ON} = V_P$. The electrical characteristics are identical with the 2 configurations. This fast turn on time added to a very low shutdown current saves battery life and brings flexibility when designing the audio section of the final application.

NCP2993 is a zero pop noise device when using a single-ended or differential audio input configuration.

Shutdown Function

The device enters shutdown mode when shutdown signal is low. During the shutdown mode, the DC quiescent current of the circuit does not exceed 100 nA. In this configuration, the output impedance is 8.5 k Ω on each output.

Current Limit Circuit

The maximum output power of the circuit ($P_{orms} = 1.0$ W, $V_P = 5.0$ V, $R_L = 8.0$ Ω) requires a peak current in the load of 500 mA.

In order to limit the excessive power dissipation in the load when a short-circuit occurs, the current limit in the load is fixed to 1.1 A. The current in the four output MOS

transistors are real-time controlled, and when one current exceeds 1.1 A, the gate voltage of the MOS transistor is clipped and no more current can be delivered.

Thermal Overload Protection

Internal amplifiers are switched off when the temperature exceeds 160°C, and will be switched on again only when the temperature decreases fewer than 140°C.

The NCP2993 is unity-gain stable and requires no external components besides gain-setting resistors, an input coupling capacitor and a proper bypassing capacitor in the typical application.

The first amplifier is externally configurable (R_f and R_{in}), while the second is fixed in an inverting unity gain configuration.

The differential-ended amplifier presents two major advantages:

- The possible output power is four times larger (the output swing is doubled) as compared to a single-ended amplifier under the same conditions.
- Output pins (OUTA and OUTB) are biased at the same potential $V_P/2$, this eliminates the need for an output coupling capacitor required with a single-ended amplifier configuration.

The differential closed loop-gain of the amplifier is given by $A_{vd} = 2 * \frac{R_f}{R_{in}} = \frac{V_{orms}}{V_{inrms}}$.

Output power delivered to the load is given by $P_{orms} = \frac{(V_{opeak})^2}{2 * R_L}$ (V_{opeak} is the peak differential output voltage).

When choosing gain configuration to obtain the desired output power, check that the amplifier is not current limited or clipped.

The maximum current which can be delivered to the load is 500 mA $I_{opeak} = \frac{V_{opeak}}{R_L}$.

Gain-Setting Resistor Selection (R_{in} and R_f)

R_{in} and R_f set the closed-loop gain of the amplifier.

In order to optimize device and system performance, the NCP2993 should be used in low gain configurations.

The low gain configuration minimizes THD + noise values and maximizes the signal to noise ratio, and the amplifier can still be used without running into the bandwidth limitations.

A closed loop gain in the range from 2 to 5 is recommended to optimize overall system performance.

An input resistor (R_{in}) value of 24 k Ω is realistic in most of applications, and doesn't require the use of a too large capacitor C_{in} .

Input Capacitor Selection (C_{in})

The input coupling capacitor blocks the DC voltage at the amplifier input terminal. This capacitor creates a

NCP2993

high-pass filter with R_{in} , the cut-off frequency is given by

$$f_c = \frac{1}{2 * \pi * R_{in} * C_{in}}$$

The size of the capacitor must be large enough to couple in low frequencies without severe attenuation.

IEC 61000-4-2 Level 4

In some particular applications, NCP2993 may need extra ESD protection to pass IEC 61000-4-2 Level 4 qualification.

Depending on the test, user can consider different level of protection:

- up to 22 pF capacitor connected between each amplifier output terminals and ground.
- Dedicated IEC filters such as ESD7.0 series from ON Semiconductor.

In any case, the protection should be placed as close as possible to the ESD stress entry point. Proper and carefull layout is a key factor to ensure optimum protection level is achieved. Designer should make sure the connection impedance between protection and ground / protection and NCP2993 is as low as possible.

ORDERING INFORMATION


| Device | Package | Shipping [†] |
|--------------|------------------------------|-----------------------|
| NCP2993FCT2G | 9-Pin Flip-Chip (Pb-Free) | 3000 / Tape & Reel |

[†]For information on tape and reel specifications, including part orientation and tape sizes, please refer to our Tape and Reel Packaging Specifications Brochure, BRD8011/D.

NCP2993

PACKAGE DIMENSIONS

WLCSP9 1.22x1.22
CASE 499BM-01
ISSUE O




NOTES:

1. DIMENSIONING AND TOLERANCING PER ASME Y14.5M, 1994.
2. CONTROLLING DIMENSION: MILLIMETERS.
3. COPLANARITY APPLIES TO SPHERICAL CROWNS OF SOLDER BALLS.

| DIM | MILLIMETERS | |
|-----|-------------|------|
| | MIN | MAX |
| A | --- | 0.66 |
| A1 | 0.17 | 0.24 |
| A2 | 0.40 REF | |
| b | 0.24 | 0.29 |
| D | 1.22 BSC | |
| E | 1.22 BSC | |
| e | 0.40 BSC | |

RECOMMENDED SOLDERING FOOTPRINT*



*For additional information on our Pb-Free strategy and soldering details, please download the ON Semiconductor Soldering and Mounting Techniques Reference Manual, SOLDERRM/D.

ON Semiconductor and are registered trademarks of Semiconductor Components Industries, LLC (SCILLC). SCILLC reserves the right to make changes without further notice to any products herein. SCILLC makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does SCILLC assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. "Typical" parameters which may be provided in SCILLC data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. SCILLC does not convey any license under its patent rights nor the rights of others. SCILLC products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the SCILLC product could create a situation where personal injury or death may occur. Should Buyer purchase or use SCILLC products for any such unintended or unauthorized application, Buyer shall indemnify and hold SCILLC and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that SCILLC was negligent regarding the design or manufacture of the part. SCILLC is an Equal Opportunity/Affirmative Action Employer. This literature is subject to all applicable copyright laws and is not for resale in any manner.

PUBLICATION ORDERING INFORMATION

LITERATURE FULFILLMENT:

Literature Distribution Center for ON Semiconductor
P.O. Box 5163, Denver, Colorado 80217 USA
Phone: 303-675-2175 or 800-344-3860 Toll Free USA/Canada
Fax: 303-675-2176 or 800-344-3867 Toll Free USA/Canada
Email: orderlit@onsemi.com

N. American Technical Support: 800-282-9855 Toll Free USA/Canada
Europe, Middle East and Africa Technical Support:
Phone: 421 33 790 2910
Japan Customer Focus Center
Phone: 81-3-5817-1050

ON Semiconductor Website: www.onsemi.com

Order Literature: <http://www.onsemi.com/orderlit>

For additional information, please contact your local Sales Representative